

# BATTERY SAVER®

## POWER SUPPLY / AUTOMATIC LOAD SWITCH



**MODEL # 091-35**

The "BATTERY SAVER" is a power supply with a transfer relay, which is installed in a vehicle to provide power for the 12 volt accessories. Whenever the 120 VAC power is applied to the vehicle, the "BATTERY SAVER" generates +12 VDC and powers the accessories. When the AC power is removed, the loads are returned to the battery. The effectiveness of the vehicle's battery charger is increased by removing all the constant loads from the battery and permitting the entire charger capacity to be utilized for battery charging. For "BATTERY SAVER" loads that do not tolerate ripple, please contact our engineering department for more information.

### **SPECIFICATIONS:**

**Input:** 120 Vac, 1 Amp Max, 12 Vdc from Battery

**Input Fuse:** 2 Amps

**Output:** 12 Vdc, 7 Amps

**Output Fuse (Recommended):** 14 Amps

**Weight:** 9 lbs

**Warranty:** 3 Years



**ENERGIZED AND READY, WHEN SECONDS COUNT**

**7 AMPS OUTPUT**

**PROVIDES D.C. POWER TO RECHARGEABLE HAND LIGHTS AND ACCESSORIES**

**AUTOMATICALLY CONNECTS LOADS TO BATTERY WHEN A.C. POWER IS REMOVED**

**LOW COST**

**3 YEAR WARRANTY**

